

TECHNICAL DATA:

YMOCA-RELAIS

Input voltage AC:	230V
Max. voltage:	250V AC / 28V DC
Powerfactor:	0,4
Max. power:	1500 VA (AC) / 165 W (DC)
Reserve:	0,15W
Terminals diameter:	max. 1,5mm ²
Frequency band:	2,4...2,483 Ghz
Max. transmission power:	+4 dBm
Switching cycles:	50.000
Consumer:	ohmic load
Temperature range:	-20 C° to +50 C°
Certificates:	CE, RoHs
Protection class:	IP20
Dimensions:	143 x 38 x 27mm
Material:	Polycarbonate
Max. housing temperature:	+60C°
Storage temperature:	-25C° to +75C°

CASAMBI



MOUNTING INSTRUCTIONS

CASA RELAIS



Herrmann-Staudinger-Straße 10 - 16
63110 Rodgau

Tel: +49 (0) 6106 -66028-50
Fax: +49 (0) 6106 -66028-70

E-Mail: sales@ropag.de
Internet: www.rp-group.com

Errors and misprints reserved! Version 02/2021 • ANL-EN-YMOCA-RELAIS

The illustration may be different as the product is constantly being developed.



DESCRIPTION:

The CASA Relais module has two independent potential-free contacts. The firmware can easily be downloaded free of charge from the "Play Store" (Google Android) or from the "App Store" (Apple) using the CASAMBI® app loaded and used. The entire configuration and settings takes place exclusively via the app.

You can obtain more information about the CASAMBI® product range from our sales team, who can also offer you complete solutions.

1

UNBOXING:

Take the product carefully out of the packaging and remove any transport protection or protective film. Before disposing of the packaging, please check that all parts of the product have been removed. Check the packaging for completeness:

1x YMOCA-RELAIS

Is everything complete? Then the assembly can begin...

2

INSTALLATION SITE:

The product is only to be used for indoor assembly.

Note that the electrical connection may only be carried out by a qualified electrician. For safe installation, the product may only be installed on a stable surface. No installation on or near (50cm) flammable materials.

3

PROGRAMMING NOTE:

- 2 potential-free contacts – connect external circuit
- Regard max. load per contact

!

SAFETY NOTICE:

Work on electrical systems and electrical equipment may only be carried out by a qualified electrician. It is essential to disconnect the electrical line from the power supply before starting installation.

DISPOSAL INFORMATION:

Do not dispose this product in household waste!

Products with the symbol WEEE, 2003/108 must be disposed at the local electronic waste disposal!

If the housing is opened, the guarantee expires!



CONNECTION PLAN:

