



No. d'art.: YMOCA-CASADIMM
Casa Trailing Edge Dimmer Bluetooth control module,
max. 150W LED / 200W ohmic, IP20

NEWS!



The CASA trailing edge dimmer is a trailing edge dimmer. Its use enables stepless dimming of trailing-edge lamps. Output power 150W LED / 200W ohmic (e.g. light bulbs). It is controlled wirelessly with the CASAMBI® app. Strain relief and terminal cover are integrated.

DONNÉES TECHNIQUES

| Données électriques | |
|-------------------------------|-----------------------|
| Tension d'entrée AC | AC 220-240V / 50-60Hz |
| Consommation en veille | 0,5 W |
| Puissance de sortie max | 150 W |
| Coupe transversale | 2,5 mm ² |
| Types de charges | Charge capacitive |
| Type de communication | Bluetooth |
| Mode de gradation | TRIAC |
| Bande de fréquence | 2,403 - 2,479 GHz |
| max. Transmettre la puissance | +4 dBm |
| CASAMBI Inside | Oui |
| Tests d'acceptation | |
| Certificats | CE |
| Classe de protection | II |
| Degré de protection (IP) | IP 20 |
| Température ambiante | -20 à +50 C° |
| Température du boîtier max. | 60 C° |



| Données physiques | |
|--------------------------------|-----------|
| Matériau du boîtier | Plastique |
| Couleur du boîtier | blanc |
| Dimensions du produit longueur | 143 mm |
| Dimensions du produit largeur | 47 mm |
| Dimensions du produit hauteur | 29 mm |
| Longueur d'emballage | 162 mm |
| Largeur d'emballage | 51 mm |
| Hauteur d'emballage | 31 mm |