



Art.-No.: YMOBM-RE-SWISSPIR-BAT CASAMBI® motion detector Swisspir

CASAMBI® motion detectors consist of integrated CASAMBI® technology and make it possible to control luminaires without wiring work. Use the CASAMBI® app to configure parameters such as brightness and automatically switching on and off at dusk or movement. This can result in savings of up to 90%. The sensors are available in various designs for ceiling mounting or recessed installation and various detection zones from 5 to 28 m.



DANE TECHNICZNE

Electrical data	
Communication type	Bluetooth
Sensor technology	wert.Sensortechnologie.Infrarot
Range	7 m
Detection angle	100 °
Frequency band	2,4...2,486 GHz
max. transmission power	+4 dBm
CASAMBI Inside	Yes
Acceptance tests	
Certifications	CE
Ingress protection (IP) rating	IP 44
Ambient temperature	-20 to +50 C°
Storage temperature	-25 to +65 C°
Physical data	
Mounting method	recessed ceiling mounted
Housing material	Tworzywo sztuczne
Housing colour	white
Height (H)	48 mm
Diameter ø	25 mm
Product weight	0,07 kg