



Art.-Nr: YMOCA-ASR-01 CASAMBI® ASR module

YMOCA ASR 01 is a Casambi-compatible 2-channel 0–10 control unit for LED loads and luminaires which can be dimmed. It can be controlled via Bluetooth. This device is intended for installation in luminaires. It must be supplied by an external 12–24 VDC power supply. If 0-10V drivers are connected to the two outputs, the YMOCA ASR 01 can be used to control the colour temperature of luminaires in addition to standard applications. Has two 0-10V channels in addition to a control connection for an external relay as well as a sensor input. Developed for installation in luminaires and should only be used in a closed system



More information

www.rp-group.com/en/item/YMOCA-ASR-01



TECHNICAL DATA

Dimensions	
Product dimensions Length	72.6 mm
Product dimensions Width	30 mm
Product dimensions Height	18 mm
Product weight	23 g
Packaging dimensions	
Weight incl. packaging	24 g
Color	
Color	white
Storage temperature range	
Storage temperature range (Min)	-25 °C
Storage temperature range (Max)	75 °C
Housing temperature	
Ambient temperature (Max)	75 °C
Electrical connection	
Connection cross-section	1.5 mm ²
Type of dimming	CASAMBI
Temperatures	
Ambient temperature (Min)	-25 °C



Ambient temperature (Max)	45 °C
CASAMBI Products	
Communication type	Bluetooth

As of: 22.01.2025 - Subject to technical changes and errors.