



Art.-Nr: YMOCA-ASR-01 CASAMBI® ASR module

YMOCA ASR 01 is a Casambi-compatible 2-channel 0–10 control unit for LED loads and luminaires which can be dimmed. It can be controlled via Bluetooth. This device is intended for installation in luminaires. It must be supplied by an external 12–24 VDC power supply. If 0-10V drivers are connected to the two outputs, the YMOCA ASR 01 can be used to control the colour temperature of luminaires in addition to standard applications. Has two 0-10V channels in addition to a control connection for an external relay as well as a sensor input. Developed for installation in luminaires and should only be used in a closed system



Więcej informacji www.rp-group.com/pl/item/YMOCA-ASR-01



DANE TECHNICZNE

Wymiary	
Długość produktu	72.6 mm
Szerokość produktu	30 mm
Wysokość produkttu	18 mm
Waga produktu	23 g
Wymiary opakowania	
Waga z opakowaniem	24 g
Kolor	
Kolor	Biała
Temperatura przechowywania	
Zakres temperatur przechowywania (min.)	-25 °C
Zakres temperatur przechowywania (max.)	75 °C
Temperatura obudowy	
Temperatura otoczenia (max.)	75 °C
Połączenie elektryczne	
Przekrój przyłącza	1.5 mm ²
Typ ściemniania	CASAMBI
Temperatury	
Temperatura otoczenia (min.)	-25 °C





Temperatura otoczenia (max.)	45 °C
Produkt CASAMBI	
Typ komunikacji	Bluetooth

Od: 22.01.2025 - Zastrzega się prawo do zmian technicznych i błędów.