



Art.-Nr: YMOCA-DAMA-MINI CASA DAMA Mini DALI control module

NEW PRODUCT! Probably available Q1 2025

The CASA DAMA Mini module has been developed especially for flush-mounted installation. It handles control of up to 15 wired DALI luminaires. This intelligent module allows the DALI luminaires to be wirelessly controlled using advanced Casambi technology. With an integrated DALI bus power supply of 30 mA, the module ensures efficient and reliable luminaire connections. Its shape makes for an easy installation process, while the compact design permits unobtrusive integration in existing light systems. This combination of wireless control and DALI connection makes the CASA DAMA Mini a perfect solution for smart lighting requirements.



More information

www.rp-group.com/en/item/YMOCA-DAMA-MINI



TECHNICAL DATA

Dimensions	
Product dimensions Length	50 mm
Product dimensions Width	48 mm
Product dimensions Height	21.6 mm
Packaging dimensions	
Packaging dimensions Length	60 mm
Packaging dimensions Width	60 mm
Packaging dimensions Height	34 mm
Weight incl. packaging	0.05 kg
Color	
Color	White
Housing material	
Housing material	Polycarbonate
Certification	
Protection type (IP)	IP20
Storage temperature range	
Storage temperature range (Min)	-25 °C



Storage temperature range (Max)	+75 °C
Housing temperature	
Housing temperature (Max)	60 °C
Electrical connection	
Connection cross-section	1.5 mm ²
Temperatures	
Ambient temperature (Min)	-20 °C
Ambient temperature (Max)	+50 °C
CASAMBI Products	
Consumption in standby mode	0.7 W
Dimming function	DALI
Communication type	CASAMBI
Frequency band	2,403 - 2,479 GHz
Max. transmission power	+4 dBm
DALI bus supply	Yes
DALI bus voltage	15V
DALI output current	30mA
Number of DALI addresses	15 pcs.
CASAMBI Repeater	Yes
Protection type (IP)	IP20
Certifications	CE, RoHS

As of: 15.04.2025 - Subject to technical changes and errors.